


## **5CCT LED Task Bar**

With its slim profile and 5 adjustable colour temperatures, the LED Task Bar is the perfect choice for the modern kitchen.





33mm (1-5/16")

20mm (13/16")



## **Features**

- Available in white finish
- 90+ CRI
- 120V Plug and cord and hardwire power cord (sold separately) Available in 6 lengths: LEDLB-5CCT-10=9 3/4 (247mm),
- LEDLB-5CCT-12=12 3/8" (315mm), LEDLB-5CCT-18=17 1/2" (445mm), LEDLB-5CCT-24=22 5/8" (575mm), LEDLB-5CCT-36=34 7/16" (875mm), LEDLB-5CCT-48=46 1/4" (1175mm)
- Easy installation
- 5 position switch for colour temperature adjustment 2700K/3000K/3500K/4000K/5000K
- Slim profile
- Dimmable with TRIAC dimmers
- Linkable up to 200W using end to end connectors or jumper cords
- 12", 18", 24" and 32" jumper cords available (sold separately)
- cETLus listed for indoor use
- 3 years limited warranty

NOTE: Only LEDLB-5CCT-18, LEDLB-5CCT-24, LEDLB-5CCT-36, and LEDLB-5CCT-48 have ON/OFF switch.

	Specifications		
Colour Temperature	2700/3000/3500/4000/5000K		
Input Voltage	120V-277V AC		
Power Consumption (W)	5/8/12/16/20W		
Lumens	LEDLB-5CCT-10 (290 LM) LEDLB-5CCT-12 (443-541 LM) LEDLB-5CCT-18 (652-771 LM) LEDLB-5CCT-24 (966-1134 LM) LEDLB-5CCT-36 (1199-1393 LM) LEDLB-5CCT-48 (1599-1892 LM)		
LEDs	SMD2835		
CRI	90+		
Life Span (hours)	35,000		
Dimmable	with TRIAC dimmers		
Beam Angle	110°		
Linkable	Up to 200W		
Limited Warranty	3 years		
Approvals	cETLus		

**Ordering Codes:** LEDLB-5CCT-10 LEDLB-5CCT-24 LEDLB-5CCT-12 LEDLB-5CCT-36 LEDLB-5CCT-18 LEDLB-5CCT-48

## **Accessories:**

(Sold Separately)



LEDLB-J-12 12" jumper cable LEDLB-J-18 18" jumper cable LEDLB-J-24 24" jumper cable LEDLB-J-32 32" jumper cable



LTSPRO-PC-72 72" power cord and plug LTSPRO-HW-72 72" power cord for hardwire



LTSPRO-JB

Hardwire junction box

With ON/OFF switch, power line mounting on the back and 2 output ports, it allows for fixtures connections with jumper cables (sold separately), on both sides of the junction box.

Project		Туре	
Date		Contact	
Notes			









